

Quick Guide to Using Your Portable 9505A Iridium Satellite Phone

TO MAKE A CALL

1. Take your activated phone **OUTSIDE** with a clear view of the sky. The 9505A will not generally work indoors; however, you may receive a weak signal while indoors, if any at all.
2. Rotate and pull out the end of the antenna so it points **STRAIGHT UP** when the phone is held at an angle to your ear.
3. Press the **POWER** button. Wait until it finds an Iridium satellite and registers onto the system. You will see "IRIDIUM" when the unit is operational.
4. Dial a phone number in "international dialing format" and press the OK button. For example, to call 617-349-3300 dial: **00 1 617 349 3300 and press 'OK'**. You can also call another Iridium based phone by dialing **00 before the satellite telephone number**. For example, to call a 12 digit Iridium phone number dial: **00 8816 414 23405 and press "OK"**.
5. Talk to your party. Remember that calls are charged based on usage per minute. (2007 costs are approximately \$1.25/minute to a landline or cell phone and \$0.85/minute to another Iridium phone.)
6. To end the call press either the 'OK' or 'C' buttons.



Well-charged battery shows **all black squares**

Best Signal Shows 5 "steps;" can work with 1 step

Power Button

TO RECEIVE A CALL

1. The phone will ring to indicate an incoming call. Simply press the "OK" button to answer.

Tip: It is possible to turn the phone ON but keep the antenna stowed in the folded non-extended position; for instance, in order to carry the phone in the belt holster. Then, when a call is received, the phone should be taken out, the antenna rotated and extended, and the call answered by pressing the "OK" button.

Note - There are two ways that a call can be placed to your Iridium phone:

- A. The caller calls into the Iridium "gateway" (from a cellular or landline phone) by dialing **1-480-768-2500** and then enters your Iridium phone number (e.g., **8816 414 23405**).
- B. The caller calls your Iridium phone directly using the "International Dialing Format" *if their phone allows*. For example, to call the Iridium phone number 881641413823, they would dial 011 8816 414 13823.

Your Iridium Phone Number is on a sticker on the rear of your phone. Example: **8816 414 23405**.

The Iridium phone numbers of other portable, as well as dispatch center/EOC fixed phones, is on a list in your case.

CHARGING BATTERY: Charge the phone for about 3-5 hours if required. The lithium-ion battery charge, while housed in the phone, can last several months. Use the travel charger or use the supplied DC car charger to charge the battery while responding to an emergency. Use the Solar panel to charge the phone when other power is not available.

IN-CAR USE: Disconnect the folding antenna, put in the little T-connector in its place, screw in the antenna cable, and place the magnetic mount antenna on your car roof. Power the phone using the cigarette lighter adapter.